## MMI 3G Emergency Update

Version 1.2 – Q1 2014 (by KG)



7.	Go to <b>System</b> $\rightarrow$ and press <b>emergencyupdate</b> , and then press <b>Yes</b> .
	EM (0.8k) - main/system(130>45:9:0)
	kind Isd [Without Trace] 1/2
	> emergencyupdate >
	internal P
8.	MMI will now reboot and enter EmergencyUpdate screen:
	MMI3G EmApp 12.13.890
	5/7 efs-system -> V321
	Erase Please Wait
	Please Note: The deletion and programming processes are performed several times, until all
	components of the MMI have been updated. Wait until the programming process is finished
	and the system automatically restarts. Your input is not necessary, the flash tool will begin
	deleting all the existing flash information in this step.
9.	Once the above step is completed the programming screen will appear:
	MMI3G EmApp 12.13.890 MU9308
	5/7 efs-system -> V321 Program
	Please Wait
	Please note: No input is necessary from you, the update tool will perform everything
	automatically.
10	Once the MMI emergency undate is completed, you will need to enter engineering menu to
10.	verify the version of your MML to do this first press <b>Setun</b> and then <b>Return</b> and hold both
	buttons down simultaneously for approx. five seconds until the display changes.
	Settings Engineering System
	Current Train Version
	Most Zugversion: E0694
	MU Software: U806
	Update
	Note: You can guit the software download process at any time by simultaneously pressing
	and holding the Tone and Back buttons for more than five seconds.
11.	If the update completed successfully then you should now proceed with map installation.